

# WT-A7183-Q11

## Cavity Band Pass Filter

### Technical Data Sheet

S/N	Item	Parameters						
1	Center Frequency(F0)	6.2GHz						
2	Pass Band Frequency	5.7 ~ 6.7GHz						
3	Pass Band Insertion Loss	≤0.8dB						
4	Pass Band Ripple	≤0.37dB						
5	Pass Band VSWR	≤1.22:1						
6	Stop Band Rejection	<table style="width: 100%; border: none;"> <tr> <td style="width: 50%; border: none;">≥80dB @ DC ~ 5.05GHz</td> <td style="width: 50%; border: none;">≥45dB @ 6.926 ~ 7.2GHz</td> </tr> <tr> <td style="border: none;">≥40dB @ 5.05 ~ 5.474GHz</td> <td style="border: none;">≥80dB @ 7.2 ~ 19GHz</td> </tr> </table>	≥80dB @ DC ~ 5.05GHz	≥45dB @ 6.926 ~ 7.2GHz	≥40dB @ 5.05 ~ 5.474GHz	≥80dB @ 7.2 ~ 19GHz		
≥80dB @ DC ~ 5.05GHz	≥45dB @ 6.926 ~ 7.2GHz							
≥40dB @ 5.05 ~ 5.474GHz	≥80dB @ 7.2 ~ 19GHz							
7	Impedance	50 Ohms						
8	Power Handling	5W Max.						
9	Connectors	SMA-Female						
10	Surface Finish	Painted Black						
11	Temperature Range	-30°C ~ +70°C						
12	Material	<table style="width: 100%; border: none;"> <tr> <td style="width: 50%; border: none;">Housing: H62 Copper alloy</td> <td style="width: 50%; border: none;">Connectors: H59 Copper, Plated ternary alloy</td> </tr> <tr> <td style="border: none;">Cover: H62 Copper alloy</td> <td style="border: none;">Other screw: Stainless Steel</td> </tr> <tr> <td style="border: none;">Tuning screw: H62 Copper alloy</td> <td style="border: none;"></td> </tr> </table>	Housing: H62 Copper alloy	Connectors: H59 Copper, Plated ternary alloy	Cover: H62 Copper alloy	Other screw: Stainless Steel	Tuning screw: H62 Copper alloy	
Housing: H62 Copper alloy	Connectors: H59 Copper, Plated ternary alloy							
Cover: H62 Copper alloy	Other screw: Stainless Steel							
Tuning screw: H62 Copper alloy								
13	Dimensions	80*16*11mm						
14	Net weight	0.086 KG						

Outline Drawing: (Dimensions Unit: mm, Dimensions Tolerance: ±0.3mm)

