

WT-A9352-Q11

Cavity Band Pass Filter

Technical Data Sheet

S/N	Item	Parameters						
1	Center Frequency(F0)	16.65GHz						
2	Pass Band Frequency	15.8 ~ 17.5GHz						
3	Pass Band Insertion Loss	≤0.8dB						
4	Pass Band Ripple	≤0.3dB						
5	Pass Band Return Loss	≥23dB (Input / Output)						
6	Stop Band Rejection	<table border="0" style="width: 100%;"> <tr> <td style="width: 50%;">≥80dB @ DC ~ 14.7GHz</td> <td style="width: 50%;">≥40dB @ 17.95 ~ 18.35GHz</td> </tr> <tr> <td>≥70dB @ 14.7 ~ 14.95GHz</td> <td>≥75dB @ 18.35 ~ 18.5GHz</td> </tr> <tr> <td>≥40dB @ 14.95 ~ 15.35GHz</td> <td>≥80dB @ 18.5 ~ 33GHz</td> </tr> </table>	≥80dB @ DC ~ 14.7GHz	≥40dB @ 17.95 ~ 18.35GHz	≥70dB @ 14.7 ~ 14.95GHz	≥75dB @ 18.35 ~ 18.5GHz	≥40dB @ 14.95 ~ 15.35GHz	≥80dB @ 18.5 ~ 33GHz
≥80dB @ DC ~ 14.7GHz	≥40dB @ 17.95 ~ 18.35GHz							
≥70dB @ 14.7 ~ 14.95GHz	≥75dB @ 18.35 ~ 18.5GHz							
≥40dB @ 14.95 ~ 15.35GHz	≥80dB @ 18.5 ~ 33GHz							
7	Impedance	50 Ohms						
8	Power Handling	5.0W Max.						
9	Connectors	Input: SMA-Male / Output: SMA-Male						
10	Surface Finish	Painted Black						
11	Temperature Range	-40°C ~ +85°C						
12	Material	<table border="0" style="width: 100%;"> <tr> <td style="width: 50%;">Housing: H62 Copper alloy</td> <td style="width: 50%;">Connectors: Stainless Steel</td> </tr> <tr> <td>Cover: H62 Copper alloy</td> <td>Other screw: Stainless Steel</td> </tr> <tr> <td colspan="2">Tuning screw: H62 Copper alloy</td> </tr> </table>	Housing: H62 Copper alloy	Connectors: Stainless Steel	Cover: H62 Copper alloy	Other screw: Stainless Steel	Tuning screw: H62 Copper alloy	
Housing: H62 Copper alloy	Connectors: Stainless Steel							
Cover: H62 Copper alloy	Other screw: Stainless Steel							
Tuning screw: H62 Copper alloy								
13	Dimensions	70*16*9.5mm						
14	Net weight	0.078 KG						

Outline Drawing: (Dimensions Unit: mm, Dimensions Tolerance: ±0.3mm)

