

WT-A2890-Q05

Cavity Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	1.05GHz
2	Pass Band Frequency	1.0~1.1GHz
3	Pass Band Insertion Loss	≤0.4dB
4	Pass Band VSWR	≤1.2:1
5	Stop Band Attenuation	≥80dB @ 2.06~4.12GHz
6	Impedance	50 ohms
7	Power Handling	Average: ≤100W / Peak: 4000W
8	Connectors	N-Female
9	Operating Temperature	-40°C ~ +80°C
10	Surface Finish	Black Paint
11	Net Weight	0.455 KG
12	Configuration	As Below (Size Unit: mm)

