

## WT-A3002-Q05

### Cavity Band Pass Filter

### Specifications

Serial	Parameters	
1	Center Frequency (F0)	1920MHz
2	Pass Band Frequency	1910~1930MHz
3	Pass Band Insertion Loss	≤1.0dB
4	Pass Band Ripple	≤0.3dB
5	Pass Band VSWR	≤1.2:1
6	Stop Band Attenuation	≥50dB @ DC~1850MHz ≥50dB @ 1990~6000MHz
7	Impedance	50 ohms
8	Power Handling	≤10W
9	Connectors	SMA-Female
10	Operating Temperature	-30°C~+80°C
11	Surface Finish	Black Paint
12	Net Weight	0.13 KG
13	Configuration	As Below (Size Unit: mm)

