

WT-A7867-S19

Comb Band Pass Filter

Technical Data Sheet

S/N	Item	Parameters						
1	Center Frequency(F0)	4025MHz						
2	Pass Band Frequency	3550 ~ 4500MHz						
3	Pass Band Insertion Loss	≤1.0dB						
4	Pass Band Ripple	≤0.65dB						
5	Pass Band Return Loss	≥20dB						
6	Stop Band Rejection	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td>≥80dB @ DC ~ 3280MHz</td> <td>≥40dB @ 4600 ~ 4690MHz</td> </tr> <tr> <td>≥30dB @ 3280 ~ 3450MHz</td> <td>≥80dB @ 4690 ~ 12000MHz</td> </tr> </table>	≥80dB @ DC ~ 3280MHz	≥40dB @ 4600 ~ 4690MHz	≥30dB @ 3280 ~ 3450MHz	≥80dB @ 4690 ~ 12000MHz		
≥80dB @ DC ~ 3280MHz	≥40dB @ 4600 ~ 4690MHz							
≥30dB @ 3280 ~ 3450MHz	≥80dB @ 4690 ~ 12000MHz							
7	Impedance	50 Ohms						
8	Power	5W Max.						
9	Connectors	SMA-Female						
10	Surface Finish	Painted Black						
11	Temperature Range	-30°C ~ +70°C						
12	Material	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td>Housing: H62 Copper alloy</td> <td>Connectors: Stainless Steel</td> </tr> <tr> <td>Cover: H62 Copper alloy</td> <td>Other screw: Stainless Steel</td> </tr> <tr> <td>Tuning screw: H62 Copper alloy</td> <td></td> </tr> </table>	Housing: H62 Copper alloy	Connectors: Stainless Steel	Cover: H62 Copper alloy	Other screw: Stainless Steel	Tuning screw: H62 Copper alloy	
Housing: H62 Copper alloy	Connectors: Stainless Steel							
Cover: H62 Copper alloy	Other screw: Stainless Steel							
Tuning screw: H62 Copper alloy								
13	Dimensions	140*18*16mm						
14	Net weight	0.23 KG						

Outline Drawing: (Dimensions Unit: mm, Dimensions Tolerance: ±0.3mm)

