

WT-A8372-Q05

Cavity Band Pass Filter

Technical Data Sheet

S/N	Item	Parameters						
1	Center Frequency(F0)	15GHz						
2	Pass Band Frequency	14.8 ~ 15.2GHz						
3	Pass Band Insertion Loss	≤0.7dB						
4	Pass Band Ripple	≤0.15dB						
5	Pass Band Return Loss	≥20dB						
6	Stop Band Rejection	<table style="width: 100%; border: none;"> <tr> <td style="width: 50%; border: none;">≥65dB @ DC ~ 13GHz</td> <td style="width: 50%; border: none;">≥35dB @ 16 ~ 17GHz</td> </tr> <tr> <td style="border: none;">≥35dB @ 13 ~ 14GHz</td> <td style="border: none;">≥65dB @ 17 ~ 35GHz</td> </tr> </table>	≥65dB @ DC ~ 13GHz	≥35dB @ 16 ~ 17GHz	≥35dB @ 13 ~ 14GHz	≥65dB @ 17 ~ 35GHz		
≥65dB @ DC ~ 13GHz	≥35dB @ 16 ~ 17GHz							
≥35dB @ 13 ~ 14GHz	≥65dB @ 17 ~ 35GHz							
7	Impedance	50 Ohms						
8	Power Handling	10W CW						
9	Connectors	SMA-Female						
10	Surface Finish	Painted Black						
11	Temperature Range	-30°C ~ +70°C						
12	Material	<table style="width: 100%; border: none;"> <tr> <td style="width: 50%; border: none;">Housing: H62 Copper alloy</td> <td style="width: 50%; border: none;">Connectors: Stainless Steel</td> </tr> <tr> <td style="border: none;">Cover: H62 Copper alloy</td> <td style="border: none;">Other screw: Stainless Steel</td> </tr> <tr> <td style="border: none;">Tuning screw: H62 Copper alloy</td> <td></td> </tr> </table>	Housing: H62 Copper alloy	Connectors: Stainless Steel	Cover: H62 Copper alloy	Other screw: Stainless Steel	Tuning screw: H62 Copper alloy	
Housing: H62 Copper alloy	Connectors: Stainless Steel							
Cover: H62 Copper alloy	Other screw: Stainless Steel							
Tuning screw: H62 Copper alloy								
13	Dimensions	40*16*9.5mm						
14	Net weight	0.044 KG						

Outline Drawing: (Dimensions Unit: mm, Dimensions Tolerance: ±0.3mm)

