

WT-A8713-S20

Comb Band Pass Filter

Technical Data Sheet

S/N	Item	Parameters						
1	Center Frequency(F0)	29.5GHz						
2	Pass Band Frequency	22 ~ 37GHz						
3	Pass Band Insertion Loss	≤1.0dB						
4	Pass Band Ripple	≤0.5dB						
5	Pass Band Return Loss	≥17dB						
6	Stop Band Rejection	<table border="0" style="width: 100%;"> <tr> <td style="width: 50%;">≥80dB @ DC ~ 19.5GHz</td> <td style="width: 50%;">≥20dB @ 38 ~ 38.5GHz</td> </tr> <tr> <td>≥50dB @ 19.5 ~ 20.5GHz</td> <td>≥40dB @ 38.5 ~ 44GHz</td> </tr> </table>	≥80dB @ DC ~ 19.5GHz	≥20dB @ 38 ~ 38.5GHz	≥50dB @ 19.5 ~ 20.5GHz	≥40dB @ 38.5 ~ 44GHz		
≥80dB @ DC ~ 19.5GHz	≥20dB @ 38 ~ 38.5GHz							
≥50dB @ 19.5 ~ 20.5GHz	≥40dB @ 38.5 ~ 44GHz							
7	Impedance	50 Ohms						
8	Power Handling	5.0W Max.						
9	Connectors	2.92mm(K)-Female						
10	Surface Finish	Painted Black						
11	Temperature Range	-30°C ~ +70°C						
12	Material	<table border="0" style="width: 100%;"> <tr> <td style="width: 50%;">Housing: H62 Copper alloy</td> <td style="width: 50%;">Connectors: Stainless Steel</td> </tr> <tr> <td>Cover: H62 Copper alloy</td> <td>Other screw: Stainless Steel</td> </tr> <tr> <td colspan="2">Tuning screw: H62 Copper alloy</td> </tr> </table>	Housing: H62 Copper alloy	Connectors: Stainless Steel	Cover: H62 Copper alloy	Other screw: Stainless Steel	Tuning screw: H62 Copper alloy	
Housing: H62 Copper alloy	Connectors: Stainless Steel							
Cover: H62 Copper alloy	Other screw: Stainless Steel							
Tuning screw: H62 Copper alloy								
13	Dimensions	70*16*9mm						
14	Net weight	0.072 KG						

Outline Drawing: (Dimensions Unit: mm, Dimensions Tolerance: ±0.3mm)

