

# WT-A8810-S20

## Comb Band Pass Filter

### Technical Data Sheet

S/N	Item	Parameters						
1	Center Frequency(F0)	6.05GHz						
2	Pass Band Bandwidth	2.1GHz (5.0 ~ 7.1GHz)						
3	Pass Band Insertion Loss	≤1.0dB						
4	Pass Band Ripple	≤0.6dB						
5	Pass Band Return Loss	≥20dB						
6	Stop Band Rejection	<table border="0" style="width: 100%;"> <tr> <td style="width: 50%;">≥80dB @ DC ~ 4.53GHz</td> <td style="width: 50%;">≥55dB @ 7.3 ~ 7.4GHz</td> </tr> <tr> <td>≥40dB @ 4.53 ~ 4.8GHz</td> <td>≥80dB @ 7.4 ~ 16.5GHz</td> </tr> </table>	≥80dB @ DC ~ 4.53GHz	≥55dB @ 7.3 ~ 7.4GHz	≥40dB @ 4.53 ~ 4.8GHz	≥80dB @ 7.4 ~ 16.5GHz		
≥80dB @ DC ~ 4.53GHz	≥55dB @ 7.3 ~ 7.4GHz							
≥40dB @ 4.53 ~ 4.8GHz	≥80dB @ 7.4 ~ 16.5GHz							
7	Impedance	50 Ohms						
8	Power Handling	5.0W Max.						
9	Connectors	SMA-Female						
10	Surface Finish	Painted Black						
11	Temperature Range	-30°C ~ +70°C						
12	Material	<table border="0" style="width: 100%;"> <tr> <td style="width: 50%;">Housing: H62 Copper alloy</td> <td style="width: 50%;">Connectors: Stainless Steel</td> </tr> <tr> <td>Cover: H62 Copper alloy</td> <td>Other screw: Stainless Steel</td> </tr> <tr> <td colspan="2">Tuning screw: H62 Copper alloy</td> </tr> </table>	Housing: H62 Copper alloy	Connectors: Stainless Steel	Cover: H62 Copper alloy	Other screw: Stainless Steel	Tuning screw: H62 Copper alloy	
Housing: H62 Copper alloy	Connectors: Stainless Steel							
Cover: H62 Copper alloy	Other screw: Stainless Steel							
Tuning screw: H62 Copper alloy								
13	Dimensions	120*18*12.5mm						
14	Net weight	0.167 KG						

Outline Drawing: (Dimensions Unit: mm, Dimensions Tolerance: ±0.3mm)

