

WT-A9622-Q09

Cavity Band Pass Filter

Technical Data Sheet

S/N	Item	Parameters						
1	Center Frequency(F0)	5100MHz						
2	Pass Band Bandwidth	220MHz (4990 ~ 5210MHz)						
3	Pass Band Insertion Loss	≤1.8dB						
4	Pass Band Ripple	≤0.7dB						
5	Pass Band Return Loss	≥23dB						
6	Stop Band Rejection	<table border="0" style="width: 100%;"> <tr> <td style="width: 50%;">≥80dB @ DC ~ 4800MHz</td> <td style="width: 50%;">≥43dB @ 5300 ~ 5400MHz</td> </tr> <tr> <td>≥43dB @ 4800 ~ 4900MHz</td> <td>≥80dB @ 5400 ~ 19000MHz</td> </tr> </table>	≥80dB @ DC ~ 4800MHz	≥43dB @ 5300 ~ 5400MHz	≥43dB @ 4800 ~ 4900MHz	≥80dB @ 5400 ~ 19000MHz		
≥80dB @ DC ~ 4800MHz	≥43dB @ 5300 ~ 5400MHz							
≥43dB @ 4800 ~ 4900MHz	≥80dB @ 5400 ~ 19000MHz							
7	Impedance	50 Ohms						
8	Power Handling	10W Max.						
9	Connectors	SMA-Female						
10	Surface Finish	Painted Black						
11	Temperature Range	-30°C ~ +70°C						
12	Material	<table border="0" style="width: 100%;"> <tr> <td style="width: 50%;">Housing: H62 Copper alloy</td> <td style="width: 50%;">Connectors: Stainless Steel</td> </tr> <tr> <td>Cover: H62 Copper alloy</td> <td>Other screw: Stainless Steel</td> </tr> <tr> <td colspan="2">Tuning screw: H62 Copper alloy</td> </tr> </table>	Housing: H62 Copper alloy	Connectors: Stainless Steel	Cover: H62 Copper alloy	Other screw: Stainless Steel	Tuning screw: H62 Copper alloy	
Housing: H62 Copper alloy	Connectors: Stainless Steel							
Cover: H62 Copper alloy	Other screw: Stainless Steel							
Tuning screw: H62 Copper alloy								
13	Dimensions	80*16*11mm						
14	Net weight	0.088 KG						

Outline Drawing: (Dimensions Unit: mm, Dimensions Tolerance: ±0.3mm)

