

WT-A9641-Q07

Cavity Band Pass Filter

Technical Data Sheet

S/N	Item	Parameters						
1	Center Frequency(F0)	9400MHz						
2	Pass Band Frequency	9300 ~ 9500MHz						
3	Pass Band Insertion Loss	≤1.2dB						
4	Pass Band Ripple	≤0.33dB						
5	Pass Band Return Loss	≥23dB						
6	Stop Band Rejection	<table border="1" style="display: inline-table; vertical-align: top;"> <tr> <td>≥80dB @ DC ~ 8900MHz</td> <td>≥20dB @ 9600 ~ 9900MHz</td> </tr> <tr> <td>≥20dB @ 8900 ~ 9200MHz</td> <td>≥80dB @ 9900 ~ 24000MHz</td> </tr> </table>	≥80dB @ DC ~ 8900MHz	≥20dB @ 9600 ~ 9900MHz	≥20dB @ 8900 ~ 9200MHz	≥80dB @ 9900 ~ 24000MHz		
≥80dB @ DC ~ 8900MHz	≥20dB @ 9600 ~ 9900MHz							
≥20dB @ 8900 ~ 9200MHz	≥80dB @ 9900 ~ 24000MHz							
7	Impedance	50 Ohms						
8	Power Handling	5.0W Max.						
9	Connectors	SMA-Female						
10	Surface Finish	Painted Black						
11	Temperature Range	-30°C ~ +70°C						
12	Material	<table border="1" style="display: inline-table; vertical-align: top;"> <tr> <td>Housing: H62 Copper alloy</td> <td>Connectors: Stainless Steel</td> </tr> <tr> <td>Cover: H62 Copper alloy</td> <td>Other screw: Stainless Steel</td> </tr> <tr> <td>Tuning screw: H62 Copper alloy</td> <td></td> </tr> </table>	Housing: H62 Copper alloy	Connectors: Stainless Steel	Cover: H62 Copper alloy	Other screw: Stainless Steel	Tuning screw: H62 Copper alloy	
Housing: H62 Copper alloy	Connectors: Stainless Steel							
Cover: H62 Copper alloy	Other screw: Stainless Steel							
Tuning screw: H62 Copper alloy								
13	Dimensions	70*16*9mm						
14	Net weight	0.067 KG						

Outline Drawing: (Dimensions Unit: mm, Dimensions Tolerance: ±0.3mm)

