

## WT-A0197-Q08

### Cavity Band Pass Filter

### Specifications

Serial	Parameters	
1	Passband Frequency	2430~2560MHz
2	Insertion Loss	≤2.0dB
3	VSWR	≤1.3:1
4	Rejection	≥52dB @ DC~2365MHz ≥52dB @ 2625~4000MHz
5	Surface Finish	Black Paint
6	Port Connectors	SMA-Female
7	Configuration	As Below

