

# WT-A0236-Q05

## Cavity Band Pass Filter

### Specifications

Serial	Parameters	
1	Passband Frequency	1717~1760MHz
2	Insertion Loss	≤3.0dB
3	Return Loss	≥18dB
4	Rejection	≥85dB @ 1527MHz ≥85dB @ 1950MHz
5	Power	10W
6	Surface Finish	Black Paint
7	Port Connectors	SMA-Female
8	Configuration	As Below

