

## WT-A0267-Q05

### Cavity Filter

### Specifications

Serial	Parameters	
1	Center Frequency (F0)	922MHz
2	3dB Bandwidth	5MHz (919.5~924.5MHz)
3	Insertion Loss	≤2.5dB@922MHz
4	VSWR	≤1.5:1@919.5~924.5MHz
5	Rejection	≥40dBc@915MHz ≥40dBc@ 930MHz
6	Impedance	50 ohms
7	Surface Finish	Black Paint
8	Connectors	N-Female
9	Net Weight	0.365 KG
10	Configuration	As Below

