

## WT-A0295-J07

### Interdigital Band Pass Filter

### Specifications

Serial	Parameters	
1	Passband Frequency	14~18GHz (F0=16GHz)
2	Insertion Loss	≤2.0dB
3	VSWR	≤2.0:1
4	Rejection	≥40dB@ DC~11.5GHz ≥40dB@ 21~22GHz
5	Surface Finish	The Original Silver Color or Black Paint
6	Connectors	SMA-Female
7	Net Weight	TBD
8	Configuration	As Below

