

# WT-A0569-Q06

## Cavity Band Pass Filter

### Specifications

Serial	Parameters	
1	Center Frequency (F0)	2405MHz
2	Bandwidth	4MHz (2403~2407MHz)
3	Insertion Loss	≤5.0dB
4	VSWR	≤1.4:1
5	Rejection	≥50dB@ F0±5MHz(2400MHz, 2410MHz)
6	Impedance	50 ohms
7	Surface Finish	Black Paint
8	Power	10W
9	ROHS	Yes
10	Connectors	SMA-Female
11	Configuration	As Below (Size Unit: mm/[inch])

