

WT-A0680-S10

Comb Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	3700MHz
2	3dB Bandwidth	≈200MHz (≈3600~3800MHz)
3	Insertion Loss at Center Frequency	≤2.0dB@3700MHz
4	VSWR	≤1.5:1 @ 160MHz Bandwidth (3620~3780MHz)
5	Rejection	≥70dB@ 500~3475MHz ≥70dB@ 3925~7500MHz
6	Impedance	50 ohms
7	Surface Finish	The Original Silver Color
8	Power Handling	10W
9	Connectors	SMA-Female
10	Configuration	As Below (Size Unit: mm)

