

WT-A0688-J11

Interdigital Band Pass Filter

Specifications

Serial	Parameters	
1	0.5dB Pass Band Frequency	450~750MHz
2	Insertion Loss	≤0.8dB
3	VSWR	≤1.7:1
4	Rejection	≥20dBc @ 400MHz ≥20dBc @ 800MHz ≥40dBc @ 350MHz ≥40dBc @ 850MHz
5	Power Handling	10 W
6	Connectors	N-Female
7	Surface Finish	Black Paint
8	Configuration	As Below (Size Unit: mm)

