

WT-A1040-Q08

Cavity Band Pass Filter

Specifications

Serial	Parameters	
1	Pass Band Frequency	1805~1880MHz (F0=1842.5MHz)
2	Insertion Loss	≤1.5dB
3	Ripple in Band	≤1.0dB
4	Return Loss	≥18dB
5	Rejection	≥70dB @ DC~1200MHz ≥40dB @ 1200~1785MHz ≥40dB @ 1920~2400MHz ≥70dB @ 2400~3000MHz
6	Impedance	50 ohms
7	Power	20 W
8	Surface Finish	Black Paint
9	Connectors	SMA-Female
10	Net Weight	0.27 KG
11	Configuration	As Below (Size Unit: mm)

