

## WT-A1128-Q05

### Cavity Band Pass Filter

### Specifications

Serial	Parameters	
1	Center Frequency(F0)	16GHz
2	Bandwidth	100MHz (15.95~16.05GHz)
3	Insertion Loss	≤1.2dB
4	VSWR	≤1.5:1
5	Attenuation	≥60dB @ F0±500MHz (DC~15.5GHz、16.5~20GHz)
6	Impedance	50 ohms
7	Surface Finish	The Original Silver Color
8	Power Handling	2W
9	Connectors	SMA-Female
10	Configuration	As Below (Size Unit: mm)

