

# WT-A1144-J13

## Interdigital Band Pass Filter

### Specifications

Serial	Parameters	
1	Center Frequency (F0)	1650MHz
2	3dB Bandwidth	666MHz ± 10MHz (1317~1983MHz)
3	Pass Band	1400~1900MHz
4	Insertion Loss	≤ 1.0dB @ 1400~1900MHz
5	Ripple	≤ 0.25dB @ 1400~1900MHz
6	VSWR	≤ 1.5:1 @ 1400~1900MHz
7	Rejection	≥ 26dB @ DC~1250MHz ≥ 26dB @ 2100~3500MHz
8	Impedance	50 ohms
9	Surface Finish	The Original Silver Color
10	Power Handling	10W
11	Connectors	SMA-Female
12	Configuration	As Below (Size Unit: mm)

