

WT-A1151-J05

Interdigital Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	1152.5MHz
2	3dB Bandwidth	≈115.25MHz (≈1094.875~1210.125MHz)
3	Insertion Loss at Center Frequency	≤1.0dB @ 1152.5MHz
4	VSWR	≤1.5:1 @ 1104.875~1200.125MHz
5	Rejection	≥40dB @ 922MHz ≥40dB @ 1383MHz
6	Impedance	50 ohms
7	Surface Finish	The Original Silver Color
8	Power Handling	2W
9	Connectors	SMA-Female
10	Configuration	As Below (Size Unit: mm)

