

WT-A1164-J07

Interdigital Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	1000MHz
2	3dB Bandwidth	≈200MHz (≈900~1100MHz)
3	Insertion Loss at Center Frequency	≤1.0dB @ 1000MHz
4	VSWR	≤1.5:1 @ 915~1085MHz
5	Rejection	≥30dB @ 810MHz ≥30dB @ 1210MHz
6	Impedance	50 ohms
7	Surface Finish	The Original Silver Color
8	Power Handling	2W
9	Connectors	SMA-Female
10	Configuration	As Below (Size Unit: mm)

