

WT-A1186-J15

Interdigital Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	9500MHz
2	Bandwidth	5000MHz (7000~12000MHz)
3	Insertion Loss	≤1.0dB
4	Ripple	≤1.0dB
5	VSWR	≤1.8:1
6	Rejection	≥20dB @ 6500MHz ≥20dB @ 12500MHz ≥55dB @ DC~6000MHz ≥55dB @ 13000~16000MHz
7	Impedance	50 ohms
8	Surface Finish	The Original Silver Color
9	Power Handling	2W
10	Connectors	SMA-Female
11	Net Weight	0.06 KG
12	Configuration	As Below (Size Unit: mm)

