

WT-A1190-S13

Comb Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	3.2GHz
2	1dB Bandwidth	200MHz (3.1~3.3GHz)
3	Insertion Loss	≤2.5dB
4	VSWR	≤1.5:1
5	Rejection	≥50dB @ F0±150MHz (DC~3.05GHz、3.35~7.0GHz)
6	Impedance	50 ohms
7	Surface Finish	The Original Silver Color
8	Power Handling	2W
9	Connectors	SMA-Female
10	Configuration	As Below (Size Unit: mm)

