

# WT-A1603-R04

## Cavity Notch Filter

### Specifications

Serial	Parameters	
1	Stop Band Frequency	2276~2280MHz (F0=2278MHz)
2	Stop Band Attenuation	≥60dB
3	Pass Band Frequency	0~2058MHz & 2498~3500MHz
4	Pass Band Insertion Loss	≤1.0dB
5	Pass Band Ripple	≤±0.5dB
6	Pass Band VSWR	≤1.5:1
7	Impedance	50 ohms
8	Surface Finish	Black Paint
9	Power Handling	≤20W
10	Connectors	SMA-Female
11	Operating Temperature	0°C~+50°C
12	Net Weight	0.135 KG
13	Configuration	As Below (Size Unit: mm)

