

WT-A2480-R09

Cavity Band Stop Filter

Specifications

Serial	Parameters	
1	Stop Band Frequency	791~821MHz
2	Stop Band Attenuation	≥45dB
3	Pass Band Frequency	DC~771MHz & 841~2200MHz
4	Pass Band Insertion Loss	≤1.5dB
5	Pass Band VSWR	≤1.5:1
6	Impedance	50 ohms
7	Surface Finish	Black Paint
8	Power Handling	≤50W
9	Connectors	N-Male / N-Female
10	Net Weight	0.95 KG
11	Configuration	As Below (Size Unit: mm)

