

WT-A2841-Q08

Cavity Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency(F0)	1880MHz
2	Pass Band Frequency	1850~1910MHz
3	Pass Band Insertion Loss	≤1.5dB
4	Pass Band VSWR	≤1.3:1
5	Stop Band Rejection	≥50dB @ F0±70MHz (DC~1810MHz、1950~4000MHz)
6	Impedance	50 ohms
7	Surface Finish	Black Paint
8	Power Handling	≤20W
9	Connectors	N-Male / N-Female
10	Net Weight	0.29 KG
11	Configuration	As Below (Size Unit: mm)

