

# WT-A2927-S07

## Comb Band Pass Filter

### Specifications

Serial	Parameters	
1	Center Frequency(F0)	1.95GHz
2	Pass Band Frequency	1.8~2.1GHz
3	Pass Band Insertion Loss	≤1.0dB
4	Pass Band VSWR	≤1.3:1
5	Stop Band Attenuation	≥40dB @ DC~1.5GHz ≥40dB @ 2.4~7.0GHz
6	Impedance	50 ohms
7	Surface Finish	Black Paint
8	Power Handling	≤10W
9	Connectors	SMA-Female (Flange Structure) [Material: Stainless Steel]
10	Net Weight	0.075 KG
11	Configuration	As Below (Size Unit: mm)



WT Microwave INC.

<http://www.wtmicrowave.com> E-mail: [tech@wtmicrowave.com](mailto:tech@wtmicrowave.com) [sales@wtmicrowave.com](mailto:sales@wtmicrowave.com)

<http://www.cdweitong.com> E-mail: [tech@cdweitong.com](mailto:tech@cdweitong.com) [sales@cdweitong.com](mailto:sales@cdweitong.com)

TEL:+86-28-84300332/84300037 FAX:+86-28-84300332-807

Add: Chengdu of China Zip Code:610051