

## WT-A2945-Q05

### Cavity Band Pass Filter

### Specifications

Serial	Parameters	
1	Center Frequency (F0)	7883MHz
2	1dB Pass Band Frequency	7783~7983MHz
3	Pass Band Insertion Loss	≤1.0dB
4	Pass Band Ripple	≤0.5dB
5	Pass Band VSWR	≤1.3:1
6	Stop Band Rejection	≥40dB @ DC~7071MHz ≥60dB @ 8691~18000MHz
7	Impedance	50 ohms
8	Power Handling	≤5W
9	Connectors	SMA-Female
10	Surface Finish	The Original Silver Color or Black Paint
11	Net Weight	0.04 KG
12	Configuration	As Below (Size Unit: mm)

