

WT-A2952-S08

Comb Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	8160MHz
2	Pass Band Frequency	7770~8550MHz
3	Insertion Loss at CF	≤1.1dB @ 8160MHz
4	Pass Band Return Loss	≥20dB
5	Pass Band Group Delay Variation	≤4.0ns
6	Stop Band Rejection	≥35dB @ 7400MHz ≥35dB @ 9000MHz
7	Impedance	50 ohms
8	Power Handling	≤5W
9	Connectors	SMA-Female
10	Surface Finish	The Original Silver Color or Black Paint
11	Operating Temperature	-10℃~+50℃
12	Net Weight	0.035 KG
13	Configuration	As Below (Size Unit: mm)

