

## WT-A2969-Q05

### Cavity Band Pass Filter

### Specifications

Serial	Parameters	
1	Center Frequency (F0)	1400MHz
2	3dB Bandwidth	≈30MHz (1385~1415MHz)
3	40dB Bandwidth	≤80MHz (1360~1440MHz)
4	Insertion Loss at F0	≤1.0dB @ 1400MHz
5	VSWR	≤1.3:1 @ 1390~1410MHz
6	Impedance	50 ohms
7	Power Handling	≤10W
8	Connectors	SMA-Female
9	Surface Finish	Black Paint
10	Net Weight	0.13 KG
11	Configuration	As Below (Size Unit: mm[inch])

