

WT-A3044-Q10

Cavity Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	9900MHz
2	Pass Band Frequency	9600~10200MHz
3	Pass Band Insertion Loss	≤0.8dB
4	Pass Band VSWR	≤1.5:1
5	Stop Band Attenuation	≥60dB @ 9300MHz ≥60dB @ 10500MHz
6	Impedance	50 ohms
7	Surface Finish	The Original Silver Color or Black Paint
8	Power Handling	≤5W
9	Connectors	SMA-Female
10	Net Weight	0.195 KG
11	Configuration	As Below (Size Unit: mm)

