

WT-A3060-J11

Interdigital Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency(F0)	1287.5MHz
2	Pass Band Frequency	1000~1575MHz
3	Pass Band Insertion Loss	≤1.0dB
4	Pass Band VSWR	≤1.5:1
5	Stop Band Rejection	≥30dB @ 900MHz ≥30dB @ 1675MHz ≥40dB @ 2*F0 (2575MHz)
6	Impedance	50 ohms
7	Power	≤2W
8	Temperature Range	-40℃~+80℃
9	Surface Finish	The Original Silver Color or Black Paint
10	Connectors	SMA-Female
11	Net weight	0.105 KG
12	Configuration	As Below (Size Unit: mm)

