

WT-A3097-Q06

Cavity Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	2715MHz
2	Pass Band Frequency	2706~2724MHz
3	Pass Bands Insertion Loss	≤2.0dB
4	Pass Bands Return Loss	≥18dB
5	Stop Band Rejection	≥15dB @ DC~2700MHz ≥15dB @ 2730~6000MHz
6	Impedance	50 ohms
7	Surface Finish	Black Paint
8	Power Handling	≤20W
9	Connectors	SMA-Female
10	Net Weight	0.2 KG
11	Configuration	As Below (Size Unit: mm)

