

WT-A3119-Q07

Cavity Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	2870MHz
2	Pass Band Frequency	2820~2920MHz
3	Pass Bands Insertion Loss	≤1.0dB
4	Pass Bands VSWR	≤1.3:1
5	Stop Band Attenuation	≥30dB @ DC~2770MHz ≥30dB @ 2970~6000MHz
6	Impedance	50 ohms
7	Surface Finish	Black Paint
8	Power Handling	≤10W
9	Connectors	SMA-Female
10	Net Weight	0.09 KG
11	Configuration	As Below (Size Unit: mm)

