

WT-A3147-Q04

Cavity Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	1575MHz
2	Pass Band Frequency	2MHz (1574~1576MHz)
3	Pass Band Insertion Loss	≤1.0dB
4	Pass Band Ripple	≤0.3dB
5	Pass Band VSWR	≤1.3:1
6	Stop Band Rejection	≥55dB @ DC~1545MHz ≥55dB @ 1605~3500MHz
7	Impedance	50 ohms
8	Power Handling	≤10W
9	Connectors	SMA-Female
10	Surface Finish	Black Paint
11	Net Weight	0.34 KG
12	Configuration	As Below (Size Unit: mm)

