

# WT-A3780-S15

## Comb Band Pass Filter

### Specifications

Serial	Parameters	
1	Center Frequency (F0)	3.2GHz
2	1dB Bandwidth	2.9~3.5GHz
3	Pass Band Insertion Loss	≤1.0dB
4	Pass Band VSWR	≤1.3:1
5	Stop Band Rejection	≥50dB @ 2.8GHz ≥50dB @ 3.6GHz
6	Impedance	50 ohms
7	Power Handling	≤200W
8	Connectors	N-Female
9	Temperature Range	-30℃~+70℃
10	Surface Finish	Black Paint
11	Net Weight	0.375 KG
12	Configuration	As Below (Size Unit: mm)

