


WT-A5055-Q05

Cavity Band Pass Filter

Specifications

Serial	Parameters	
1	Center Frequency (F0)	401.5MHz
2	Pass Band Frequency	400~403MHz
3	Pass Band Insertion Loss	≤2.0dB
4	Pass Band VSWR	≤1.3:1
5	Stop Band Rejection	≥35dB @ Fc ± 8MHz (DC~392MHz、411~800MHz)
6	Impedance	50 ohms
7	Power Handling	≤50W
8	Connectors	N-Female
9	Surface Finish	Black Paint
10	Temperature Range	-10°C ~ +50°C
11	Net Weight	0.53 KG
12	Configuration	As Below (Size Unit: mm)



WT Microwave INC.

<http://www.wtmicrowave.com> E-mail: tech@wtmicrowave.com sales@wtmicrowave.com

<http://www.cdweitong.com> E-mail: tech@cdweitong.com sales@cdweitong.com

TEL: +86-28-84300332/84300037 FAX: +86-28-84300332-807

Add: Chengdu of China Zip Code: 610051