

WT-A8382-Q08

Cavity Band Pass Filter

Technical Data Sheet

S/N	Item	Parameters
1	Center Frequency(F0)	12.45GHz
2	Pass Band Frequency	12.2 ~ 12.7GHz
3	Pass Band Insertion Loss	≤1.0dB
4	Pass Band Ripple	≤0.25dB
5	Pass Band Return Loss	≥20dB
6	Stop Band Rejection	≥90dB @ DC ~ 11.25GHz ≥90dB @ 13.65 ~ 25GHz
7	Impedance	50 Ohms
8	Power Handling	5.0W Max.
9	Connectors	SMA-Female
10	Surface Finish	Painted Black
11	Temperature Range	-30°C ~ +70°C
12	Material	Housing: H62 Copper alloy Connectors: Stainless Steel Cover: H62 Copper alloy Other screw: Stainless Steel Tuning screw: H62 Copper alloy
13	Dimensions	70*16*9mm
14	Net weight	0.07 KG

Outline Drawing: (Dimensions Unit: mm, Dimensions Tolerance: ±0.3mm)

